

- 3-Axis Joystick Keyboard
- Steel Frame Design
- Setting up ID Address from 1 ~ 255 for Speed Dome Camera or Receiver
- Control Pan/Tilt, Focus, Zoom, Iris and other parameter setup
- LCD Menu, easy to operate
- Camera Setup, Camera Address, Preset, Auto tour, Auto Scan.
- Control Range: 1200m (RS485)
- Controls up to 32 Dome Cameras



## Specification

Signal System

Functions on Keyboard:

Protocol:

Baudrate Communication:

Communication Distance:

Power :

Weight:

Size:

## Detail

RS 485

PTZ Commands: CALL, PRESET, SHOT

Camera Commands: WIDE/TELE , FAR/NEAR, CAM/ID, AUTO, OPEN/CLOSE

Other Functions: ON/OFF, LIVE/TAPE, F1, F2, F3, SEQ/MUL

Multiplexer view: FUNC/ Full Screen, 4x4, 2x2, 3x3, PIP

Numbers: 1~9 and Clear/Enter

1 Dipswitch set 1~8

Multiprotocol , Compatible with PELCO-D Protocol

2 sets of RS485 block connector

1 RJ11 RS485 Connector

2400BPS, 4800BPS, 9600BPS, 19200BPS

1200m - 3936Ft

DC12V 800mA

2Kg - 4Lbs

380 x 165 x 80(mm)